

Missing key

error message:

```
Sub-process /usr/bin/sqv returned an error code (1), error message is:
Missing key 827C8569F2518CC677FECA1AED65462EC8D5E4C5, which is needed to
verify signature.
```

Some genius changed the key...

```
sudo curl -fsSL https://archive.kali.org/archive-key.asc | gpg --dearmor -o
/etc/apt/trusted.gpg.d/kali.gpg
```

Fsck at boot

Once the node didn't start and was complaining /dev/sda1 had errors. **At boot:** press "e" to edit Grub's line starting with linux and remove quiet splash to put single fsck.... like:

```
linux /boot/vmlinuz-<version> root=UUID=<your-uuid> ro single
fsck.mode=force fsck.repair=yes
```

And voilà !

Power Management ethX

Ethernet card switches off after a long period of inactivity?

```
ethtool -s <interface_name> wol d
```

Make it permanent:

```
vi /etc/udev/rules.d/70-disable-ethernet-power-management.rules
```

```
ACTION=="add", SUBSYSTEM=="net", KERNEL=="eth*", RUN+="/usr/sbin/ethtool -s
%k wol d"
ACTION=="add", SUBSYSTEM=="net", KERNEL=="enp*", RUN+="/usr/sbin/ethtool -s
%k wol d"
```

```
udevadm control --reload-rules
```

From:

<https://wiki.fortier-family.com/> - **Warnaud's Wiki**

Permanent link:

<https://wiki.fortier-family.com/os/kali/sysadmin>

Last update: **2025/05/23 12:22**

